

Racquets

ProKennex 2013 KM FFT F165
ProKennex 2013 Kinetic KM FFT F175
ProKennex 2013 FFT Carbon 195
ProKennex 2012 KM FFT F185
ProKennex 2012 KM FFT F175
ProKennex 2012 KM FFT F165

Tension	Pattern	Start M's	Mains Skip
28-38	14 x 18	H	NONE

Length 1pc	
Short Side	
Length 2pc	20' x 18'
Tie Off M's	3T
Start 1pc X	
Last 1pc X	
Tie 1pc X	
Start 2pc X	6H
Last 2pc X	6T
Tie 2pc X	4H, 8T

Notes	<p>Shared holes at 4T,5T & 6H,7H Alternate stringing 2-3 mains on each side. Feed first left main from 1HL through 1TL and loop around to 2TL to 2HL for second main. Continue to 3HL down to 3TL for third main. Loop around to 4TL (lower hole) to 4HL for fourth main. Continue feeding string through 5HL to 4TL (upper hole) for fifth main. Loop around to 5TL (upper hole) to 6HL for sixth main. Continue string through 7HL to 5TL (lower hole) for seventh (final) main. Follow same procedure on right side but reverse level of entry on shared holes; i.e., Loop around to 4TR (upper hole) to 4HR for fourth main. Start 1X with an easy weave.</p>
--------------	---